



P R E S T I G E

L E D L I G H T I N G

Vivid 288 LED Dual Blinder

USER MANUAL





1. SUMMARY

1. Parameter

Voltage: AC110-240V 60Hz/50Hz

Lamp: D3296: 96pcs 3W RGB 3 in 1 / 288W

Total power: 330W

Channel: 14CH

Function DMX Signal Auto-run Master/Slave

2 . Display Function



Menu 1 : A001 is DMX address , press Enter to edit the address. You can press Down or Up to select address , and save it by Enter , display strobe is no signal.

Menu 2 : Press Esc ,then Down or UP till shows : Auto , then press Enter to the auto-run.

Menu 3 : Press Esc and then Down or UP till shows : Audi , then press Enter to Built-in voice-driven program.

Menu 4 : Press Esc and then Down or UP till shows: ALL, Then Enter all Brightness.

Menu 5 : Press Esc then Down or UP till shows : SPEd, press Enter to speed control , Down or UP to select page speed , 31 level speed to adjust(0-30),00 shows the fastest , and 30 shows the most slowest.

3 . DMX512 CH Control (Total 14 channels)

CH1----- 0-9 Blank (10-91)Strobe (92-255) Auto-run

CH2-----0-255 Master Dimming

CH3-----0-255 Red Dimming

CH4-----0-255 Green Dimming

CH5-----0-255 Blue Dimming

CH6—1 macro effect (0-36) no bright (37-73) red (74-110) green (111-147) blue (148 -185) macro effect (186-255) all bright

CH7—2 macro effects (0-36) no bright (37-73) red (74-110) green (111-147) blue (148 -185) effect (186-255) all bright



P R E S T I G E

LED LIGHTING

- CH8—3 macro effects (0-36) no bright (37-73) red (74-110) green (111-147) blue
(148-185) macro effect (186-255) all bright
- CH9—4 macro effects (0-36) no bright (37-73) red (74-110) green (111-147) blue (148
-185) macro effect (186-255) bright
- CH10--5 macro effect (0-36) no bright (37-73) red (74-110) green (111-147) blue (148
-185) macro effect (186-255) all bright
- CH11--6 macro effects (0-36) no bright (37-73) red (74-110) green (111-147) blue
(148 -185) macro effect (186-255) all bright
- CH12--7 macro effects (0-36) no bright (37-73) red (74-110) green (111-147) blue
(148 -185) macro effect (186-255) all bright
- CH13--8 macro effects (0-36) no bright (37-73) red (74-110) green (111-147) blue
(148 -185) macro effect (186-255) bright
- CH14—0-255 1~8 circular effect